

Huawei Technologies Co.,Ltd.
 Level 5,TowerA, 799 Pacific Highway, Chatswood 2067
 Tel: 1800 046 639
 Web: <https://solar.huawei.com/au>



Huawei Inverter – AS4777.2:2020 Firmware Compliance Update

For SUN2000-50KTL-M0 and SUN2000-100KTL-M1, these two models has to be manually upgraded to following version to guarantee inverters comply with AS4777.2 2020 standards which takes effect from 18th DEC 2021.

Model	SUN2000-50KTL-M0	SUN2000-100KTL-M1
Compliance Version	V300R001C00SPC127 and later	V500R001C00SPC120 and later


Download link for SUN2000-50KTL-M0 firmware package V300R001C00SPC127

https://solar.huawei.com/-/media/Solar/attachment/pdf/au/service/download/SUN2000V300R001C00SPC127_package_50KTL.zip

Download link for SUN2000-100KTL-M1 firmware package V500R001C00SPC120

https://solar.huawei.com/-/media/Solar/attachment/pdf/au/service/download/SUN2000V500R001C00SPC120_package_100KTL.zip


Manual firmware update can be completed through Maintenance > Upgrade Device > Inverter Upgrade > Select V300R001C00SPC127 for 50KTL-M0 or V500R001C00SPC120 for 100KTL-M1 as target version.




For L0, L1, M1, M2 and M3 series, FusionSolar APP will push a mandatory firmware update the first time FusionSolar APP locally connects to the inverter hotspot and accesses to device commissioning page. Please ensure FusionSolar is updated to the latest version from 18th DEC 2021 and onwards.

To download or upgrade to the latest APP FusionSolar

- Step 1 Enter the website at solar.huawei.com





- Step 2 Tap Download FusionSolar APP to go to the download page
- Step 3 For Android users, APP can be downloaded from browser directly (.apk file) or through Huawei AppGallery. For iOS users, APP is available in App Store.




Locally accesses to device commissioning

APP FusionSolar will automatically detect current inverter's firmware version and push an upgrade message and this compulsory firmware upgrade cannot be bypassed.



After firmware upgrade is completed, please select the correct grid code from 4 new sets of grid codes (AUSTRALIA AS4777_A-LV230, AUSTRALIA AS4777_B-LV230, AUSTRALIA AS4777_C-LV230, and AUSTRALIA AS4777_NZ-LV230) based on the region of installation to make inverter fully compliant.

AS/NZS 4777.2:2020 requires inverter shall not operate until a regional setting has been selected and activated by an authorised person.



Should you have any questions please feel free to contact Huawei local hotline 1800719871 Monday to Friday 9am to 6pm (AEST) excluding public holidays.

Yours sincerely,

Derek Wang

Service manager - HUAWEI TECHNOLOGIES (AUSTRALIA) PTY LTD

13/12/2021